What to Check When Your Dashboard Warning Light Comes On

That sudden glow of an orange or red icon on your dashboard can be unsettling. Many drivers react by booking a repair straight away, but a little diagnosis beforehand can save time and money. Understanding what the light means and what to check before you call a garage puts you in a stronger position. It also helps you avoid unnecessary work or, worse, ignoring a genuine fault.

Know the Colour Code

Not every warning light signals an emergency. Modern cars use a simple colour system. Red means stop or address the issue immediately. Amber or yellow means something needs attention soon but the car is safe to drive for a short while. Green or blue lights are informational, telling you a system is active. The first step in any diagnosis is noting the colour. If the light is red, pull over when it is safe and switch off the engine. If amber, you can drive carefully to a safe place to investigate.

Look Up the Symbol

Car manufacturers use dozens of symbols, and the same shape can mean different things on different models. The owner's manual is the best reference. If you do not have a paper copy, most manuals are available online through the manufacturer's website or motoring databases. Take a photo of the symbol on your phone and match it to the manual. This simple check tells you whether the problem is something minor, like a low washer fluid level, or something serious, like an engine overheating warning. Knowing the exact symbol prevents guesswork.

Check Fluid Levels and Simple Mechanicals

Many warning lights relate to fluids that you can check yourself. The most common are engine oil, coolant, and windscreen washer fluid. Park on level ground, let the engine cool if it has been running, and inspect the dipstick and coolant reservoir. Low oil can trigger an amber oil can symbol. Low coolant appears as a thermometer in wavy lines. If either is low, topping up may turn the light off. Also check the brake fluid reservoir, usually a translucent plastic tank near the back of the engine bay. If the level is too low, the brake warning light may stay on. Never open the radiator cap when the engine is hot, as the system is pressurised. If the fluid level is fine but the light remains, the sensor or a leak may be the cause.



Tyres also have their own warning. A tyre pressure monitoring system (TPMS) light looks like a cross-section of a tyre with an exclamation mark. Use a reliable pressure gauge to check each tyre when cold. Inflate to the pressure stated in the manual or on the driver's door pillar. If the light goes out after a short drive, the problem was simply low pressure. If it stays on, there may be a slow puncture or a faulty sensor.

Listen and Feel for Symptoms

A warning light rarely appears without some change in how the car behaves. When you see a light, pay attention to engine noise, vibration, steering response, and braking feel. A rumbling noise combined with a brake system warning light strongly suggests worn brake pads or a problem with the brake discs. A rough idle and the check engine light together point to an engine management issue such as a failing sensor or a vacuum leak. Noting these symptoms helps the garage diagnose the fault faster and gives you a clearer picture of urgency. If the car feels normal and the light is amber, you have more time to investigate.

Consider the Electrical System

Modern cars rely on dozens of sensors, and sometimes a warning light comes on because of a glitch rather than a real fault. A weak battery, a loose battery terminal, or a recent jump start

can confuse the voltage-sensitive electronics. If the battery symbol lights up, check that the terminals are clean and tight. A multimeter reading of 12.4 volts or higher with the engine off suggests the battery is healthy. If the light stays on while driving, the alternator may be failing. Similarly, the check engine light can be triggered by a loose fuel cap. Tighten it until it clicks, then drive for a few cycles. The light should reset on its own. If it does not, the fault is more permanent.

Know When to Call a Professional

Some warning lights require expert diagnosis. The most serious is the engine overheat warning, often a red thermometer symbol. If this comes on, stop the engine immediately. Do not drive further. Check the coolant level once the engine is cool. If it is low, topping up might solve it, but if the level is correct and the light stays on, the engine may have a real cooling system fault such as a failed thermostat, a blocked radiator, or a broken water pump. Driving with an overheating engine can cause permanent damage.

Another example is the airbag warning light. This indicates a fault in the safety restraint system. Airbag components are sensitive and can deploy accidentally if handled incorrectly. A qualified technician should read the fault codes and carry out any repairs. The same applies to the transmission warning light, which on many cars appears as a gear shape with an exclamation mark. Transmission repairs are complex and involve high-pressure hydraulic systems or precise electronic controls. Attempting a DIY fix on these can lead to injury or costly mistakes.



The check engine light, often accompanied by a code such as P0420 or a generic "engine fault" message, should be read with a diagnostic tool. Many independent garages offer a free or low-cost code reading service. A code like P0420 points to a failing catalytic converter, which is a significant repair. A code like P0301 points to a misfire on cylinder one, which might be a simple spark plug change or a more involved injector problem. Knowing the code helps you decide whether the garage needs to investigate further or whether a simple fix like a new sensor will do the job.

Use a Systematic Approach Before Booking

Rather than rushing to book a repair, work through a logical sequence. Start with the manual. Then check fluids, tyre pressures, and the battery. Listen and feel for symptoms. If the issue is still unclear, note the exact symbol and any diagnostic codes. This information is valuable to any technician. A garage that receives a clear description of the problem can prepare the right parts and tools, reducing the time your car spends off the road. It also means you are less likely to be sold a repair you do not need.

For Scottish motorists, local independent garages are often the best choice for this kind of diagnosis. They combine experience with a personal service that can save you money and hassle. Publications such as pentlandpress.co.uk regularly cover advice on finding trustworthy independent garages and understanding common car faults. Their guidance on vehicle maintenance and repairs is written with the Scottish driver in mind, covering everything from

MOT preparation to electric car care. Checking a warning light yourself before you call a garage is a practical step that puts you in control. It also makes the conversation with the technician more productive. You are not just saying "the light came on" - you are saying "the engine oil warning light came on, the oil level is correct, and I hear a ticking sound from the front of the engine." That level of detail helps everyone.

Some drivers worry that a warning light means the car is unsafe to drive. That is rarely true for an amber light. The car's computer will often reduce power or limit speed to protect the engine, a feature called limp mode. In limp mode the car can still be driven slowly to a garage or home. If you are unsure, a phone call to the garage can clarify. Most will give a quick opinion over the phone without charging.



Finally, keep a record of any warning lights that appear regularly. A pattern of the same light coming back after a repair suggests the underlying issue was not fully fixed. That is a sign to seek a second opinion or to ask the garage to revisit the work. A responsible independent garage will stand by its repairs. Reading resources like pentlandpress.co.uk can help you find a garage with a good reputation for honesty and competence.

In short, a dashboard warning light is a signal, not a verdict. By spending ten minutes on your own checks, you can often avoid a costly repair that was not needed, or you can arrive at the garage with a clear description of the real problem. That is better for your wallet and for the health of your car.

Pentland Press News on social media Facebook